

CLAIM AMENDMENTS

1 1. (Canceled)

1 2. (Currently amended) A method for use in wireless equipment, the method
2 comprising the steps of:
3 receiving a signal;
4 processing the received signal to generate a Yamamoto-Itoh (YI) metric,
5 determining a Bit-Error-Rate (BER) estimate for the received signal as a function
6 of the YI metric,
7 wherein the determining step further comprises the steps of:
8 retrieving, from at least one look-up table stored in a memory, a value for a
9 compensation factor as a function of a value of the generated YI metric and an initial
10 BER estimate as a function of the generated YI metric; and
11 modifying the initial BER estimate value with the retrieved compensation factor
12 value to determine the BER estimate.

1 3. (Previously presented) A method for use in wireless equipment, the method
2 comprising the steps of:
3 processing a received signal to generate at least one Yamamoto-Itoh (YI) metric
4 value over a time period;
5 selecting a compensation factor value as a function of the generated YI metric
6 value;
7 selecting an initial BER estimate value as a function of the generated YI metric
8 value; and

9 determining a Bit-Error-Rate (BER) estimate for the received signal as a function
10 of the initial BER estimate value and the selected compensation factor value.

1 4. (Previously presented) The method of claim 3 wherein the determining step
2 further includes the step of multiplying the selected compensation factor value by the
3 initial BER estimate value to determine the BER estimate.

1 5. (Previously presented) A method for use in wireless equipment, the method
2 comprising the steps of:

3 processing a received signal to determine an initial BER estimate value for the
4 received signal;

5 modifying the initial BER estimate value for the received signal with a
6 compensation factor value to provide a Bit-Error-Rate (BER) estimate for the received
7 signal, wherein the compensation factor value is determined as a function of at least
8 one Yamamoto Itoh (YI) metric value.

1 6. (Canceled)

1 7. (Currently amended) Apparatus for use in wireless equipment, the
2 apparatus comprising:

3 a convolutional decoder for processing a received signal for use in determining at
4 least one Yamamoto-Itoh (YI) metric value,

5 a processor for determining a Bit-Error-Rate (BER) estimate for the received
6 signal as a function of the at least one YI metric value,

7 wherein the processor (a) retrieves, from at least one look-up table stored in a
8 memory, a compensation factor value as a function of the at least one YI metric value

9 and an initial BER estimate value as a function of the at least one YI metric value, and
10 (b) modifies the initial BER estimate value with the retrieved compensation factor value
11 to determine the BER estimate.

1 8. (Previously presented) Apparatus for use in wireless equipment, the
2 apparatus comprising:
3 a convolutional decoder for processing a received signal for use in determining at
4 least one Yamamoto-Itoh (YI) metric value,
5 a processor for determining a Bit-Error-Rate (BER) estimate for the received
6 signal as a function of the at least one YI metric value,
7 wherein the processor (a) determines a compensation factor value as a function
8 of the at least one YI metric value, (b) determines an initial BER estimate value as a
9 function of the at least one YI metric value, and (c) determines the BER estimate for the
10 received signal as a function of the initial BER estimate value and the selected
11 compensation factor value.

1 9. (Previously presented) The apparatus of claim 8 wherein the processor
2 multiplies the selected compensation factor value by the initial BER estimate value to
3 determine the BER estimate.

1 10. (Canceled)

1 11. (Previously presented) A wireless receiver comprising:
2 a memory for storing a look-up table such that an index into the look-up table is a
3 Yamamoto-Itoh (YI) metric value for retrieving an initial Bit-Error-Rate (BER) estimate
4 stored therein; and

5 a processor for modifying the initial BER value with a scale factor to determine a
6 Bit-Error-Rate (BER) estimate for a received signal.

7 12. (Previously presented) A method for use in wireless equipment, the method
8 comprising the steps of:

9 processing a received signal to generate a Yamamoto-Itoh (YI) metric,

10 determining an initial Bit-Error-Rate (BER) estimate value for the received signal
11 as a function of the YI metric,

12 selecting, as a function of the generated YI metric, a value for a compensation
13 factor; and

14 modifying the initial BER estimate value with said compensation factor value to
15 determine the BER estimate.